

B11 Torpedotip E12 or E26 Base






Lorem ipsum

Key Features & Benefits

The new 120V E12 or medium E26 base **B11 (torpedo tip)** LED series integrates a set of filament LED sources and is ideal to replace **incandescent** bulbs. Available: 2W, 4W, 6W options. This series LED light bulbs are highly versatile, which can be in lanterns, fan or chandelier fixtures and offer significant energy savings and environmentally friendly. Light output is 360° which is perfect for even dispersion applications.

Technical Specifications

Model Name	JQ-CE12-A02K27	JQ-CE12-A04K27 JQ-CE26-A04K27	JQ-CE12-A06K27 JQ-CE12-A06K50 JQ-CE26-A06K27 JQ-CE26-A06K50
Photo			
Halogen Replacement	25 Watt	40 Watt	50 Watt
Operating Voltage:	120AC	120 AC	120 AC
Power consumption:	2 Watt	4 Watt	6 Watt
Dimmable: *	Yes	Yes	Yes
Dimensions:	3.58" x 1.25"D	3.58" x 1.25"D	3.58" x 1.38"D
CRI:	85	85	85
CCT Option:	2700K	2700K	2700K, 5000K
Luminous Flux:	200 lm.	360 lm.	480 lm.
Operating Temperature:	-20° C- +50° C	-20° C- +50° C	-20° C- +50° C
Storage Temperature	-30° C- +60° C	-30° C- +60° C	-30° C- +60° C
Safety Certification:	FCC Compliance	ETL, FCC Compliance	FCC Compliance
Rated Lifespan:	>15,000hrs.	>15,000hrs.	>15,000hrs.

Notes Wattage +/- 10%; Lumen Values +/- 5Lms. CRI +/- 5% ; Dimmable* fully tested with LUTRON © DVCLDVCL etc.

JQ Green America Inc.

San Diego Office: (714)837-7155; (760)300-9233

Fax: (888)653-8693

Miami Office: (786)397-0999; (772)301-2967

New York Office: (856)200-1091; (215)239-0594

© Copyright 2018 JQ Green America Inc.